DOCUMENT DETAILS
Document version 1.0
Updated 9th August 2018

PRODUCT DETAILS
ICE Zodiac
ICE Zodiac HS

TECHNICAL SUPPORT
www.progressive-id.co.uk
support@progressive-id.co.uk
Tel: 01732 850070

ICE Zodiac How to create parameter archive

How to connect to the ICE Coder

Step 1) Plug a FAT32 formatted USB into the port on the printer. Wait 1 minute, you will see a USB stick icon flash top right of the screen.

Step 2) Open up the tools/setting menu using the top right icon

Step 3) Browse through the options 'Setup' → 'Control' until you see an option worded 'Clarity Parameter Archive' (or similar)

Step 4) Click on this top option to open the parameter backup screen, then using the bottom buttons, choose 'create archive'

Step 5) Keep name as is, but take a note of which coder has this name, click ok. The coder will backup the parameters to the USB and let you know when finished. Unplug usb, return to PC and access the file through Clarity Config Manager.

Step 6) Adjust settings in file and save.

Step 7) Return to Ice coder and reverse the above procedure selecting Restore from Archive instead of Create Archive.